

40961



- b) i) A PCM system has a uniform quantizer followed by a v bit encoder. Show that the rms signal to noise ratio is approximately given by $(1.8 + 6v)$ dB, assuming a sinusoidal input. (7)
- ii) Show that the signal to noise power ratio of a uniform quantizer is PCM system increases significantly with increase in number of bits per sample. Also determine the signal to quantization noise ratio of an audio signal $S(t) = 4 \sin(2\pi 500t)$ which is quantized using a 10 bit PCM. (6)
12. a) Explain the construction features and working of Adaptive Delta Modulation. (13)
- (OR)
- b) Elucidate a DPCM system. Derive the expression for slope overload noise of a system. (13)
13. a) What is the need for line shaping of Signals ? Derive the PSD of a unipolar RZ and NRZ, line code and compare their performance. (13)
- (OR)
- b) What is ISI and what are the various methods to remove ISI in communication system. Also state and prove Nyquist first criterion for Zero ISI. (13)
14. a) i) Calculate the BER for a Binary Phase Shift Keying modulation from first principles. (7)
- ii) Derive the expression for bit error probability of a QPSK system. (6)
- (OR)
- b) i) Draw and explain the Quadrature Receiver structure for coherent QPSK. (6)
- ii) Draw the signal space diagram of a coherent QPSK modulation scheme and also find the probability of error if the carrier takes on one of four equally spaced values $0^\circ, 90^\circ, 180^\circ$ and 270° . (7)
15. a) i) Find the (7, 4) systematic and non-systematic cyclic code words of the message word 1101. Assume the generator polynomial as $1 + x^2 + x^3$. (7)
- ii) Develop the Code for an (n, k) linear cyclic code and explain its working. (6)
- (OR)
- b) i) Explain Viterbi algorithm with an appropriate coder and a received input word of length 12. Assume a coder of constraint length 6 and rate efficiency $\frac{1}{2}$. (7)
- ii) What is the need of Digital Modulations in digital communication ? Explain any one modulation scheme in detail. (6)

PART - C

(1×15=15 Marks)

16. a) Explain about Pseudo noise sequences with examples and mention their importance. (15)
- (OR)
- b) Explain in detail about digital hierarchy with examples.