

9. What is the need for antialiasing filter ?
10. If the spectrum of a sequence $x(n)$ is $X(e^{j\omega})$, then what is the spectrum of the signal down sampled by 2 ?

PART - B (5 × 16 = 80 Marks)

11. (a) (i) State and prove if $x_3(K) = x_1(K) x_2(K)$, then $x_3(n) = \sum_{m=0}^{N-1} x_1(m) x_2((n-m))_N$. (6)
- (ii) Using the equation given in 11(a)(i), for the 8 point DFT of the sequence $x(n) = 1, 0 \leq n \leq 3$
 $0, 4 \leq n \leq 7$, compute the DFT of $x_1(n) = 1, n = 0, 1 \leq n \leq 4$
 $1, 5 \leq n \leq 7$. (10)

OR

- (b) (i) Compute the 8 point circular convolution $x_1(n) = \{1, 1, 1, 1, 0, 0, 0, 0\}$
 $x_2(n) = \sin \frac{3\pi n}{8}, 0 \leq n \leq 7$ using matrix method. (12)
- (ii) State the differences between (a) overlap-save (b) overlap-add. (4)

12. (a) If $H_a(S) = \frac{1}{(S+1)(S+2)}$, find the corresponding $H(z)$ using impulse invariant method for sampling frequency of 5 samples/second. (16)

OR

- (b) Write down steps to design digital filter using bilinear transform technique and using this design a HPF with a pass band cutoff frequency of 1000 Hz & down 10 dB at 350 Hz the sampling frequency is 5000 Hz. (16)

13. (a) Design a filter with $H_d(e^{jw}) = e^{-j3w}$, $-\frac{\pi}{4} \leq w \leq \frac{\pi}{4}$

$$= 0, \frac{\pi}{4} < |w| \leq \pi$$

Using a Hamming window with $N = 7$.

(16)

OR

- (b) Consider the transfer function $H(z) = H_1(z) \cdot H_2(z)$ where $H_1(z) = \frac{1}{1 - \alpha_1 z^{-1}}$ and

$$H_2(z) = \frac{1}{1 - \alpha_2 z^{-1}}. \text{ Find the output round off noise power by assuming } \alpha_1 = 0.5,$$

$$\alpha_2 = 0.6.$$

(16)

14. (a) Draw the quantization noise model for a second order system

$$H(z) = \frac{1}{1 - 2r \cos \theta z^{-1} + r^2 z^{-2}} \text{ and find the steady state output noise variance. (16)}$$

OR

- (b) Explain the characteristics of limit cycle oscillation with respect to the system described by the difference equation $y(n) = 0.95 y(n-1) + x(n)$. Determine the dead band of the filter.

(16)

15. (a) For the signal $x(n]$, obtain the spectrum of down sampled signal $x(Mn)$ and

$$\text{upsampled signal } x\left(\frac{n}{L}\right)$$

(16)

OR

- (b) Discuss in detail about any two applications of adaptive filtering with a suitable diagram.