

12. (a) Derive an expression for capacitance of a coaxial cable. (16)

Or

- (b) (i) Derive an expression for Polarization 'P'. (4)
(ii) State and explain the electric boundary conditions between two dielectrics materials. (12)
13. (a) From Biot Savart's law obtain expression for magnetic field intensity and vector potential at a point P and distance ' R ' from infinitely long straight current carrying conductor. (16)

Or

- (b) (i) Consider two identical circular current loops of radius 3 m and opposite current 20 Amps are in parallel planes, separated on their common axis by 10 m. Find the magnetic field intensity at a point midway between the two loops. (8)
(ii) State Biot-Savart's law. Find the magnetic Field intensity at the origin due to current element $Id\vec{l} = 3\pi(\hat{a}_x + 2\hat{a}_y + 3\hat{a}_z) \mu A.m$ at (3, 4, 5) in free space. (8)
14. (a) (i) A charged particle with velocity \vec{u} is moving in a medium containing uniform field $\vec{E} = E\hat{a}_x V/m$ and $\vec{B} = B\hat{a}_y Wb/m^2$. What should \vec{u} be so that the particle experiences no net force on it? (8)
(ii) State and derive the magnetic boundary conditions between the two magnetic mediums. (8)

Or

- (b) Derive the expression for inductance and magnetic flux density inside the solenoid. Calculate the inductance of the solenoid and energy stored when a current of 8 A flowing through the solenoid of 2m long, 10 cm diameter and 4000 turns. (16)
15. (a) (i) State and prove Poynting's theorem and give its physical interpretation. (8)
(ii) Derive Maxwell's equations for time varying fields. (8)

Or

- (b) Derive the wave equation starting from Maxwell's equation for free space. (16)