

PART B — (5 × 13 = 65 marks)

11. (a) Relate Nyquist rate criteria and aliasing effect with sampling process. Discuss how aliasing error can be avoided. (13)

Or

- (b) Determine the Region of Convergence of the following signal using z transform :

(i) $x(n) = u(-n)$. (4)

(ii) $x(n) = u(l-n)$. (4)

(iii) $x(n) = (2)^n u(-n)$. (5)

12. (a) (i) Summarize the properties of DFT. (6)

- (ii) Determine the circular Convolution of the following system

(1) $x(n) = \{1, 2, 3\}$ and $h(n) = \{1, 2, 1\}$. (3)

(2) $x(n) = \{4, 1, 2, -3\}$ and $h(n) = \{1, -1, 2\}$. (4)

Or

- (b) (i) Compute the DFT of given sequence using DIF-FFT algorithm.

$x(n) = \{1, 2, 3, 4, 4, 3, 2, 1\}$. (8)

- (ii) Determine the IDFT of $X(k) = \{6 - 2 - 2j, 2 - 2 + 2j\}$ using DIT algorithm. (5)

13. (a) Compute a Chebyshev analog lowpass filter transfer function by using bilinear transformation technique for the following specification ($T = 1$ sec).

$$0.8 \leq |H(e^{j\omega})| \leq 1, \quad 0 \leq \omega \leq 0.2\pi$$

$$|H(e^{j\omega})| \leq 0.2, \quad 0.6\pi \leq \omega \leq \pi. \quad (13)$$

Or

- (b) Design a Butterworth digital lowpass filter using impulse invariant technique with $T = 1$ sec satisfying the following specification. (13)

$$0.8 \leq |H(e^{j\omega})| \leq 1 \quad 0 \leq \omega \leq 0.25\pi$$

$$|H(e^{j\omega})| \leq 0.15 \quad 0.65\pi \leq \omega \leq \pi$$

14. (a) Design an Ideal highpass filter with frequency response using hamming window

$$H_d(e^{j\omega}) = \begin{cases} 0, & -\frac{\pi}{2} \leq \omega \leq \frac{\pi}{2} \\ 1, & \frac{\pi}{2} \leq |\omega| \leq \pi \end{cases}$$

Plot the magnitude response for $N = 7$. (13)

Or

- (b) Design an ideal lowpass filter with frequency response using rectangular window.

$$H_d(e^{j\omega}) = \begin{cases} 1, & -\frac{\pi}{4} \leq \omega \leq \frac{\pi}{4} \\ 0, & \frac{\pi}{4} \leq |\omega| \leq \pi \end{cases} \quad (13)$$

Plot the magnitude response for $N = 11$.

15. (a) (i) Define Quantization noise. Derive the quantization noise power. (5)
(ii) Compute the coefficient quantization error of given second order IIR filter system by both direct and cascade form. Assume $b = 3$ bits. (8)

$$H(z) = \frac{1}{(1 - 0.95z^{-1} + 0.255z^{-2})}$$

Or

- (b) (i) Determine the limit cycle oscillations and deadband of the following first order IIR filter. Truncated bit $b = 3$. (8)

$$y(n) + 0.95y(n-1) = x(n)$$

Input to the system is

$$x(n) = \begin{cases} 0.875, & n = 0 \\ 0, & \text{otherwise} \end{cases}$$

- (ii) Discuss the overflow error signal scaling. (5)